

xxf~::~x~xxf~::ffxxxxxf~fffx~xx~xxxx~xx~::~xx~::fx~\xx~f~::~xxf

RLETRM / Documentation
Copyright 1988 Michael D. Ward

RLETRM is a "no frills" terminal emulator for the Color Computer. A 32K CoCo-1, CoCo-2, or a CoCo-3 is the minimum requirement. It is designed to let you display RLE files online by Just <R>eadin9 the file. Examples of such files can be found in the Graphics Data Library. They have extensions of .RLE and may be located quickly by using the command BRO *.RLE In addition, hi-res weather radar maps on Page AWX-4 may be viewed online. Note that only PMODE-4 is supported. RLETRM.BIN is supplied configured for 8-bit, no Parity. This may be changed with the configuration Program RLETRM.BAS if necessary.

The Graphic may be saved after viewing. If a disk ROM is Present the Disk-save option will be selected automatically. If no disk ROM is Present TAPE-save will be used instead. In either case the Graphic will be saved as a binary file with an extension of /BIN as the default for disk users.

300/1200/2400 baud are supported with an RS232 PAK. If no PAK is Present 300 baud serial I/O will be used instead. The PBJ WordPak-I or -II will also be supported if either is Present.

The following Control keys function as follows:

The "Down-Arrow" key is the "Control" key.

- SAVE Graphic file.....Cntl-1
- Toggle Baud Rate.....Cntl-2
- Toggle Color Set.....Cntl-3
- View Last Graphic.....Cntl-4
- Display this Menu.....Cntl-7
- Interrupt Graphic.....Break
- Restore Text Screen.....Cntl-@
- Exit to Basic.....Cntl-0

Control-3 (Toggle Color Set) also functions in "View Last Graphic mode".

Two other keys may be used to send Pre-defined strings. They are control-6 and control-8. Any string up to 31 characters long may be sent with either key.

The Program RLETRM.BAS may be used to define these strings and imbed them into RLETRM. RLETRM.BAS may also be used to set the default baud rate and Parity setting for the RS232 Pak.