

VIP Writer™

Quick Reference Card

TEXT MODE COMMAND SUMMARY

Command	Key(s)
Block Copy	(CLEAR)–(X)
Block Delete	(CLEAR)–(V)
Block Move	(CLEAR)–(M)
COMMAND Mode	(CLEAR)–(CLEAR)
Continue Locate	(CLEAR)–(C)

CURSOR CONTROL

Down	(DOWN ARROW)
Left	(LEFT ARROW)
Left One Word	(CLEAR)–(Q)
Right	(RIGHT ARROW)
Right One Word	(CLEAR)–(W)
Up	(UP ARROW)
Left Screen	(CLEAR)–(LEFT ARROW)
Right Screen	(CLEAR)–(RIGHT ARROW)
Top of textfile	(CLEAR)–(SHIFT)(UP ARROW)
End of textfile	(CLEAR)–(SHIFT)(DOWN ARROW)
Home	(CLEAR)–(SHIFT)(LEFT ARROW)
Bottom of Screen	(CLEAR)–(SHIFT)(RIGHT ARROW)

Delete Functions

Delete Character	(CLEAR)–(D)
Delete to End of Line	(CLEAR)–(S)
Delete line	(CLEAR)–(F)
Delete Block Markers	(CLEAR)–(Y)
Delete to Beginning of line	(CLEAR)–(A)
Delete Word Left	(CLEAR)–(H)
Delete Word Right	(CLEAR)–(J)
FUNCTION E	(CLEAR)–(E)
FUNCTION R	(CLEAR)–(R)
FUNCTION T	(CLEAR)–(T)
HELP	(CLEAR)–(?)
INSERT Character	(CLEAR)–(I)
INSERT Line	(CLEAR)–(O)
LOCATE OR CHANGE	(CLEAR)–(L)
Memory Left, Used	(CLEAR)–(;))
MASK Case (during locate)	(CLEAR)–(–)
Page Back	(CLEAR)–(UP ARROW)
Page Ahead	(CLEAR)–(DOWN ARROW)
PRINT (from cursor)	(CLEAR)–(P)–(P)
PROGRAMMABLE Function	(CLEAR)–(Z)
Repeat last function	(SHIFT)–(@)
TAB (5, 8, 16, 24, etc.)	(SHIFT)(LEFT ARROW)
Verify Locate	(CLEAR)–(ENTER)
Window Mode	(CLEAR)–(P)–(W)

LOCATE OR CHANGE

Locate (CLEAR)–(L)–(text string*)
 Continue Locate (CLEAR)–(C)
 Locate Masked String (CLEAR)–(–)**
 Locate–Wild Card (CLEAR)(L)–(**ΔΔ**)
 Locate & Change (Single occurrence)
 (CLEAR)–(L)–(locate string*)–(UP ARROW)–
 (change string*)–(DOWN ARROW)
 Locate & Change (Multiple execution)
 (CLEAR)–(L)–(locate string*)–(UP ARROW)–
 (change string*)–(UP ARROW)–(# of changes)
 (use 999 for whole file)
 Verified Multiple Execution
 Command Mode–(CLEAR)(ENTER)**
 Locate & Delete
 (CLEAR)–(L)–(locate string*)–(UP ARROW)–
 (DOWN ARROW)
 Locate & Delete (multiple execution)
 (CLEAR)–(L)–(locate string*)–(UP ARROW)–
 (UP ARROW)–(#) (or 999)

*up to 21 characters long

**this command toggles on and off

PARAMETER FORMAT COMMANDS

Parameter	Default Value	Limits
AL Auxiliary A Line	0	1-255 0=SUP
BL Auxiliary B Line	0	1-255 0=SUP
AS Auxiliary A Status	A	A, E, 0
BS Auxiliary B Status	A	A, E, 0
BD Baud Rate	3	1=110, 2=300, 3=600 4=1200, 5=2400
FL Footer Line	62	1-22 0=SUP
FS Footer Status	A	A, E, 0
HL Header Line	4	1-255 0=SUP
HS Header Status	A	A, E, 0
IP Invisible Print	N	Y or N
JU Justify	Y	Y or N
LD Line Delay	0	0-255
LF Linefeeds	N	Y or N
LS Line Spacing	1	1-255
BM Bottom Margin	60	2-254
LM Left Margin	8	0-255
RM Right Margin	72	10-255
MT Margin Top	6	1-253
NP No-Print Print	N	Y or N
NL Nulls	0	0-255
PL Page Length	66	3-255
PN Page Number	1	1-65535
PG Page Number Line	0	1-255 0=SUP
PP Page Number Placement	C	L, C, R, T
PC Print Comment	N	Y or N
PH Printer Handshaking	Y	Y or N
PA Single Sheet Pause	N	Y or N

A=ALL; E=EVEN; 0=ODD; Y=YES; N=NO; L=LEFT
 C=CENTER; R=RIGHT; T=TOGGLE; SUP=SUPPRESS

MISTAKE SAVERS

Help	(CLEAR)-(H)
Restore character/line	(CLEAR)-(G)
Restore text buffer	O-O-P-S (ENTER)

COMMAND MODE COMMAND SUMMARY

Command	Key(s)
Alternate Markers	(A)-(ENTER)
Cassette Load	(C-L)-(ENTER)
Cassette Name	(C-N)-(ENTER)
Cassette Save	(C-S)-(ENTER)
Change Display Color	(C)-(ENTER)
Character Size -64 display	(6-4-W/N)-(ENTER)
Clear Textfile	(C-L-E-A-R)-(ENTER)
Clear Text after Cursor	(A-F-T-E-R)-(ENTER)
Clear Text before Cursor	(B-E-F-O-R-E)-(ENTER)
Display Print Parameters	(.)-(ENTER)
Dump Hi-Res Display	(D-U-M-P)-(ENTER)
Exit Command Mode	(/)-(ENTER)
Exit to Basic	(E-N-D)-(ENTER)
Extra Memory	(D-U-M-P)-(ENTER)
Invert Display	(I)-(ENTER)
"OOPS" Buffer Recall	(O-O-P-S)-(ENTER)
Reset Print Parameters	(@)-(ENTER)
Reset Linking List	(;)-(ENTER)
Screen Display Mode	(32/51/64/85)-(ENTER)
Tab Defaults	(T-A-B)-(ENTER)
Toggle (block move)	(B-L-O-C-K)-(ENTER)
Toggle Key Beep	(B-E-E-P)-(ENTER)
Toggle Word Wrap Around	(W-R-A-P)-(ENTER)
Width- Edit Window	(W-I-D-T-H)-(ENTER)
Word Count	(W-O-R-D)-(ENTER)

DMP-200 PRINTER DRIVER

Function	Decimal	Key(s)
Bold On	27 31	(CLEAR)-(1)
Bolf Off	27 32	(CLEAR)-(2)
Underline On	15	(CLEAR)-(3)
Underline Off	14	(CLEAR)-(4)
Forward Linefeed	27 54	(CLEAR)-(5)
Reverse Linefeed	27 10	(CLEAR)-(6)
Condensed Print	27 20	(CLEAR)-(7)
Standard Print	27 19	(CLEAR)-(8)
Elongation On	27 14	(CLEAR)-(9)
Elongation Off	27 15	(CLEAR)-(:)

WINDOW MODE COMMAND SUMMARY

FORMAT WINDOW	(CLEAR)-(P)-(W)
EXIT FORMAT WINDOW	(E)
(UP ARROW)	Scrolls to top of previous page
(DOWN ARROW)	Scrolls down 12/17/20 lines
(LEFT ARROW)	Scrolls left 16 characters
(RIGHT ARROW)	Scrolls right 16 characters
(SHIFT)(UP ARROW)	Displays first page
(SHIFT)(DOWN ARROW)	Displays next page
(SHIFT)(LEFT ARROW)	Displays left side of page
(ENTER)	Displays carriage returns

MARKER SUMMARY

Marker	Key	Display	Function
Auxiliary A**	"<"	3/4 yellow	Marks line to be Aux. A
Auxiliary B**	">"	3/4 red	Marks line to be Aux. B
Block (0-9)	(b)	orange	Marks block of text (2 req.)
Center	(u)	blue	Centered line
Comment	(+)	green diag.	Not printed
Flush Right**	"<"	red diag.	Flush right marg.
Footer	(.)	red	Marks line to be used as footer
Format	(k)	magenta	Altered Format Parameters
Formfeed	(/)	cyan	Bring paper to top
Header	(.)	yellow	Marks line to be used as header
Link**	">"	blue diag.	Line with file- name to link
No Print	(n)	3/4 orange	Mark print start and end
Nonspace	(space)	dark hue	No spacing
Pause Print	(=)	orange diag.	Printer pause
P Code	(0)	buff	Printer codes

**FLUSH RIGHT and LINK marker alternate with AUXILIARY A&B with (CLEAR) (CLEAR)-(A)-(ENTER)

BLOCK MANIPULATION

Block Marker	(CLEAR)-(B)
(must be used before & after text to be moved)	
Delete Block Markers	(CLEAR)-(Y)
Block Marker (multiple)	(CLEAR)-(B)-(0-9)
Delete All Block Markers	(CLEAR)-(Y)-(*)
Block Copy	(CLEAR)-(X)
Block Move	(CLEAR)-(M)
Block Delete	(CLEAR)-(V)

Note: When in the ten block mode, you must respond to the number of executions to take place when prompted.

MERGING FOR CENTERING

ELONGATED	5 C.P.I.	LM0, RM40
ELONGATED-COMPRESSED	8.3 C.P.I.	LM0, RM67
NORMAL (STANDARD)	10 C.P.I.	LM0, RM72
TWELVE PITCH	12 C.P.I.	LM0, RM96
FIFTEEN PITCH	15 C.P.I.	LM0, RM120
COMPRESSED	16.7 C.P.I.	LM0, RM132