

11. CONFIG is ready to begin creating your customized System Master diskette. If you have one drive, the screen tells you that the DESTINATION diskette is your blank, formatted diskette and that your SOURCE diskette is the BASIC09/CONFIG diskette. Place your formatted diskette in the drive, and press **[C]**. You'll swap between the formatted diskette and the BASIC09/CONFIG diskette several times.

If you have a two-drive system, place a formatted diskette in Drive /D1, and press the space bar. The screen tells you that OS-9 is:

```
GENERATING NEW BOOT
.... PLEASE WAIT
```

12. Following the boot file generation, a menu lets you select the commands you want to include on your system diskette. You have the following choices: none; the full set of commands; or a set consisting of commands you choose individually. The menu looks like this:

```
CONFIG

DO YOU WISH TO ADD
[N]O COMMANDS, STOP NOW
[F]ULL COMMAND SET
[I]NDIVIDUALLY SELECT
[H] RECEIVE HELP
SELECTION [N,F,I,H]
```

Most people like to choose the individual commands they want to use. For the time being, press **[F]** to include the full set. Later, you can create another custom diskette that has only the commands you need.